



T.			U_f	I_f	Cl.	U_a	U_{g2}	U_{g3}	U_{g1}	I_a	I_{g2}	I_{g1}	$U_{g1 \approx}$	P_{dr}	P_o	P_{g2}	P_a
			V	A		V	V	V	V	mA	mA	mA	V	W	W	W	W
OS 125/2000	Tu	1	10	5	C-Tgr	2000	400	45	-100	170	60	10		1,6	250		
					C-Tlf	1500	400	45	-100	135	54	10	1,6	150	(A-Mod)		
						2000	400	45	-55	80	18	2	0,5	60	(G ₁ -Mod)		
$S = 4,5 \text{ mA/V}; \mu_{(g2/g1)} = 10,5; f = 50 \text{ MHz}$																	
5 C/101 A	STCE	1	10	5	C-Tgr	2000	400	45	-100	150	55	13			210		
					C-Tlf	2000	400	-45	-100	85	65	13		60	(G ₃ -Mod)		
						2000				150	$S = 5,4 \text{ mA/V}; f = 20 \text{ MHz}$				100		
5 T 250 A 1	Maz	2	10	5	C-Tgr	1250	500	40	-90	160	45	12	175	2	130		
						1500	500	40	-90	160	45	12	175	2	160		
						2000	500	40	-90	160	45	12	175	2	210		
						2000	600	500	-500	175	50	maximum		30	125		
					C-Tgr Fig. 1	1250	150	150	-90	160	15	28	190	4,6	130		
						1500	150	150	-90	160	15	27	190	4,4	160		
						2000	150	150	-90	160	15	26	190	4,4	210		
						2000	600	600	-500	175	50	maximum		30	125		
					C-Tlf A-Mod	1250	350	100	-80	150	50	30	200	6	120		
						1600	400	100	-80	150	45	25	190	5	155		
$S = 4,5 \text{ mA/V}; \mu_{(g2/g1)} = 10,5; f = 50 \text{ MHz}$																	
332 A	WE	3	10	5	C-Tlf Fig. 1	1250	130	130	-180	150	75	45	305	15	125		
						1600	130	130	-180	150	75	45	320	15	155		
						1600	500	500	-500	160	50	maximum		30	85		
803	int	1	10	5	C-Tlf G ₁ -Mod	1250	500	40	-100	130	30	8	160	4	52		
						1500	550	40	-90	110	25	6	130	3	53		
						2000	600	40	-80	80	20	4	100	2	53		
						2000	600	500	-500	160	maximum			20	125		
					C-Tlf G ₃ -Mod Fig. 2	1250	(13 kΩ)	-70	-110	100	70	22	200	4	40		
						1500	(17 kΩ)	-90	-100	100	70	20	190	3,5	50		
						2000	(35 kΩ)	-110	-100	80	48	15	170	2,5	53		
$S = 4 \text{ mA/V}; \mu_{(g2/g1)} = 14; f = 20 \text{ MHz}$																	
stat					B-Tlf	1250	500	40	-30	130	33	8	90	4,5	52		
						1500	550	40	-35	110	30	5	70	3	53		
						2000	600	40	-40	80	20	3	55	1,5	53		
						2000	600	500	-500	160	maximum			20	125		

T.	C_{g1}	C_a	$C_{g1/a}$
	pF	pF	pF
RK 28	15	15	0,02
RK 28 A	15	15	0,02
803	17	29	0,15
4069 A	18	13	0,1

Equivalents

PC 2/500	Phi = 803	322 A	WE = 803
RK 28	Ray = 5 C/101	3069 A	LMT = 5 C/101 A
RK 28 A	Ray = 803	3069 B	LMT = 5 C/101 A
5 T 250 AO	Maz = 803	4069 A	STCE = 5 C/101 A

